

# MODEL 6



**CHARVEL**  
BY JACKSON / CHARVEL

## General Specifications

**Tremolo:** Kahler™ Standard  
**Body Composition:** Poplar  
**Neck/Fingerboard Composition:** Rock Maple through Body Neck/  
Quarter-Sawn Rosewood  
**Machine Heads:** Jackson SG38-07B  
**Fingerboard Nut Composition:** Phenolic  
**Fret Wire:**  
**Hardness—** Rockwell C6/Brinell 171  
**Size—** .118 × .114 × .51 × .37  
**Composition—** 18% Nickel Silver  
**Finish Options:** Black, Pearl White, Red, Cobalt Blue, Black Cherry  
**Control Functions:** One Volume, One Tone, Jackson Pre-Amp with Mid Boost, Three 2-Way Mini-Toggles

## Pickup Specifications

<b>Model Number:</b>	J200[Two]	J50B[One]
<b>Description:</b>	Dual Coil, Bi-Level Hum-bucking. Designed for use with active circuitry.	Accented High frequency Bridge position Hum-bucking. Designed for use with active circuitry.
<b>Sr [In K Hz]:</b>	9.90	6.58
<b>Z [ @ Sr in MOhms]:</b>	1.8	5.9
<b>Inductance [In Henries]:</b>	2.4	5.3
<b>Q [ @ Sr]:</b>	12.6	2.64
<b>Output Level [ @ Sr]:</b>	+44.1dB	+56.4dB
<b>Magnetic Structure:</b>	Alnico V	Ceramic
<b>Resistance [In KOhms]:</b>	11.65	8.58